## Technical data sheet

# PERMACOL® 5198-SERIES



## **DESCRIPTION**

The PERMACOL 5198 A/B series are polyurethane adhesives which can be applied for binding, repair and fill materials as: metals, plastics, mineral substrates, wood and fire resistant building boards. These adhesives cure at room temperature, so full cure takes place at 20°C. At higher temperatures the adhesive will have a shorter pot life and cure time.

## **BENEFITS**

- Suitable for outside applications
- Solvent free
- Very low shrinkage
- O Resistant to temperature fluxes
- O Resistant to oil, grease and acids

Туре	Pot life (at 23°C)	Curing time (at 23°C)	Final strength after (at 23°C)
5198-3	ca. 1.5 min	ca. 3 min	ca. 24 uur
5198-5	ca. 5 min	ca. 20 min	ca. 24 uur
5198-7	ca. 7 min	ca. 30 min	ca. 24 uur
5198-10	ca. 10 min	ca. 30 min	ca. 24 min
5198-15	ca. 15 min	ca. 45 min	ca. 24 min
5198-30	ca. 20 min	ca. 60 min	ca. 24 uur
5198-60	ca. 60 min	ca. 180 min	ca. 24 uur

Technical details			
Mixing ratio	A:B=1:1 (weight, volume)		
Viscosity A-component	17.000 mPa.s (D=30/s 23°C)		
Viscosity B-component	17.500 mPa.s (D=30/s 23°C)		
Minimum application temperature	15°C		
Colour mixture	Slight yellow		
Hardness	70 shore D		
Temperature resistance	-30°C up to +100°C		
Shear Strengths			
Steel – Steel	72 kg/cm <sup>2</sup>		
Aluminium – Aluminium	68 kg/cm <sup>2</sup>		
Hard PVC – Hard PVC	80 kg/cm <sup>2</sup> *		
ABS – ABS	45 kg/cm <sup>2</sup> *		
PMMA – PMMA	82 kg/cm <sup>2</sup>		
* means material breakage			

## **USAGE INSTRUCTIONS**

Make sure the substrates are clean and free from dust, water, grease, fingerprints, oil, etc. Metals are to be sanded to remove the oxide layer before cleaning. Weigh the components according to the mixing ratio and mix until a homogeneous colour is reached, or use a double syringe and static mixer. Place the cartridge into a dispenser gun. Remove the cap from the syringe. Dispense a small amount from the syringe until adhesive is flowing from both sides of the cartridge (do not use this for adhesion). Connect the mixer. Dispense and discard the first mL of adhesive. Begin applying adhesive to the substrate. Do not use these adhesives at temperatures below 5°C.

### **CLEANING**

Uncured adhesive can be removed and cleaned by means of solvents as Ethanol, Acetone, Isopropanol (IPA) or MEK. Cured adhesives must be removed mechanically.

## **STORAGE**

Store in its original packaging frost free and dry. See packaging for the expiration date. Shelf life: 6 months.

## SAFETY

Use protective gloves to avoid direct contact with the skin. Check the Material Safety Data Sheet for specific safety information.

As from 24 August 2023 adequate training is required before industrial or professional use.

## **PACKAGING**

The PERMACOL 5198 series are available in different kinds of cartridges.

#### Legal Disclaimer

The products of Permacol (the "Supplier"), are sold subject to the supplier's standard conditions of sale, which are included in applicable sales agreements, printed on the back side of invoices, or available upon request. Although the information, recommendations or advice contained herein is given in good faith, supplier makes no warranty or guarantee, express or implied, (I) that the results described herein will be obtained under end-use conditions, or (II) as to the effectiveness or safety of any design incorporating supplier's products, recommendations or advice. Nothing in this or any other document shall alter, vary, supersede or operate as a waiver of any of the supplier's standard conditions of sale.

Each user bears the full responsibility for making its own determination as to the suitability of Supplier's products, recommendations or advice for its own particular purpose. Each user must identify and perform tests and analyses sufficient to assure it that its finished parts will be safe and suitable for use under end-use conditions. Because actual use of products by the user is beyond the control of Supplier, such use is within the exclusive responsibility of the user, and Supplier cannot be held responsible for any loss incurred through incorrect or faulty use of the products. Further, no statement contained herein concerning a possible or suggested use of any product is intended or should be construed to grant any license under any patent or other intellectual property right of Supplier, or as a recommendation for the use of such material in the infringement of any patent or other intellectual property right.